## Audio

**Class-D digital amplifier.** 125W/Ch at 8 ohms

**Line-In Sources Supported:** Audio device with analog RCA output or optical output (optical adaptor required). TV device with HDMI ARC or optical output (optical adaptor required).

**Subwoofer output:** Auto-detecting RCA type, user-adjustable 50-110 Hz crossover

**Speaker output connections:** Banana plugs (2) capable of stereo or dual mono sound.

**Adjustable bass and treble controls** to optimize sound performance. Adjust volume by individual room or by groups of rooms.

## Physical

**Dimensions - H x W x D**
2.52 x 8.54 x 8.54 in. (64 x 217 x 217 mm).

**Weight**
4.6 lbs. (2.1 kg).

**Product finish**
Black

**Controls**
Touch interface with volume up/down, previous/next track and play/pause.

## Power & Networking

**Power supply**
AC 100-120/220-240 V, 50-60 Hz

**WiFi**
Connects to your home Wi-Fi network with any 802.11 b/g/n router. 802.11n only network configurations are not supported—you can either change the router settings to 802.11 b/g/n or connect a Sonos product to your router.

**Ethernet ports**
Dual Ethernet ports can connect Amp to a wired home network and allow for connection of additional Sonos players.

**System requirements**
Passive speakers with speaker wire, broadband internet, and Sonos app.

## Contents

Sonos Amp, Sonos banana plugs (2), AC power cord, warranty and regulatory booklet, and Quickstart Guide.